



**A Portable Actuator for Remotely Operating
Square D Type SE
Low Voltage Circuit Breakers**



Model SE-06
User's Manual



User's Manual
Model SE-06

- 1.0 Arc-blast Hazards**
- 2.0 Application Information**
- 3.0 Safety Information**
- 4.0 Battery Information**
- 5.0 Control Cable**
- 6.0 Controller**
- 7.0 Underside Illuminator**
- 8.0 Attaching and Removing the Actuator**
- 9.0 Sequence of Operation**
- 10.0 Care and Storage**
- 11.0 Warranty**
- 12.0 Specifications**
- 13.0 Troubleshooting**

1.0 Arc-blast Hazards

The hazards associated with electrical arc-blasts are well documented. Studies conducted by numerous industries and professional organizations have sought to quantify the intensity of arc-blast, the risks to personnel, and various methodologies for mitigating the risks.

Without doubt, increasing the distance between the arc and a human is the single greatest favorable factor in reducing injuries.

The Chicken Switch® is not a panacea but rather one more tool available for protecting workers while they are performing electrical switching.

Using a Chicken Switch® may not negate the need for additional personal protective measures. The user is ultimately responsible for evaluating each situation to determine if additional protective measures are needed.




WARNING

Electrical switching may present risk of serious injury or death. This device should only be used by qualified persons after careful analysis of the hazards.

2.0 Application Information

The SE06 is suitable for Square D 'SE' non-racking circuit breakers that do not have a permanently mounted lockout device on the "OPEN" button.

It is imperative that the face plate of the SE breaker is in good condition. The portion of the breaker faceplate that is contacted by the SE06 and surrounding enclosure must be free of dirt and obstructions such as laminated labels or other non-OEM objects.



3.0 Safety Information

ALWAYS connect the control cable to the actuator and controller BEFORE installing the Chicken Switch®.

3.1 Finger pinch points

Use caution when attaching the Chicken Switch® to the breaker or while placing it near a ferrous surface.



3.2 CAUTION: Strong magnets

Keep fingers clear of the bottom of the actuator when the actuator is near a ferrous surface.

The holding magnets are very strong. Avoid placing the Chicken Switch® near electro-mechanical protective relays.

4.0 Battery Information

4.1 Battery Requirements


- Eight (8) AA alkaline cells are required.
- Carefully observe polarity when installing cells.
- Rechargeable NiMh or NiCd batteries can be used.

4.2 Battery Life

- A set of fresh alkaline cells should yield hundreds of operations.
- The Chicken Switch® is designed as a *portable* device. It is not designed to remain with the control unit connected to the actuator for extended periods of time. To do so will deplete a fresh set of batteries in approximately four to five days.


4.3 Battery Replacement

- ALWAYS disconnect the control cable before replacing batteries to avoid possible static damage of the electronics!




- Turn the control station upside down, remove the endplate retaining knob. Remove the endplate and slide the cover out as shown.

4.4 To connect/disconnect batteries:




5.0 Control Cable

5.1 Connecting the control cable



1. Align the arrow on the cable end with the top of the receptacle.
2. Push in and engage the threads on the coupling nut and turn clockwise.
3. After one or two turns of the coupling nut, push in on the cable end. Repeat this until the connector is fully seated.
4. Use a similar technique of turn-stop-and-pull to disengage the cable ends.

6.0 The Controller



The controller is designed for two-hand operation for the purpose of preventing inadvertent operation of the actuator. See the following section for a detailed description of the controller indicators and switches.

6.1 The indicator lights & controls

NOTE: Red and Green indicator lights only work when the ENABLE button is depressed.

GREEN: indicates the actuator is being commanded to extend the ON actuator.

RED: indicates the actuator is being commanded to extend the OFF actuator.

YELLOW: indicates the hand-held controller is powered and is ready.

Rapidly blinking YELLOW indicates the battery voltage with zero load has fallen to an unacceptable level. Operation is inhibited until batteries with an acceptable voltage level are installed.

The ENABLE button:

The Enable button must be continuously depressed in order to command the actuator.

Releasing the enable button has the same affect as releasing either the ON or OFF buttons – both actuators will move to the retracted position.

Note:

If either of the actuators are held in the extended position for longer than approximately 2 seconds the actuator will de-energize and will remain in extended position. When the pushbutton or the enable button is released, the actuator will retract.

7.0 Underside Illuminator

An LED light assembly is permanently installed on the underside of the Chicken Switch® actuator. This light can be used to assist with aligning and attaching the actuator in low light conditions. It also allows the user to more easily see the breaker contact position indicator when the actuator is on the breaker.


The LED light is powered from the same batteries that the Chicken Switch® uses for operating the actuator.

The LED light is lit anytime the control cable is connected. The current draw is minimal and the intent is to make the Chicken Switch® as easy to use for the operator as possible. With this design, the operator does not have to worry about turning the light on or having separate batteries for the light.

8.0 Attaching and Removing the Actuator


8.1 Pre-use Checks:

BEFORE attaching the actuator, ensure the CLOSE and TRIP plunger are fully retracted:




8.2 To Attach the Actuator





Using the black handles hold the Chicken Switch® at a slight angle and align the top angle of the Chicken Switch® on the ledge immediately below the trip unit.



Rotate the bottom of the Chicken Switch® downward toward the breaker until it is held flush against the face of the circuit breaker.



8.3 To Remove the Actuator



9.0 Sequence of Operation:

Steps	See Section for more
1. Connect the control cable to the actuator first. Then connect the other end to the Control Station. Note that the actuators will move to the retracted position if they are not already in the retracted position.	5.0
2. Visually verify that the CLOSE and TRIP plungers are fully retracted (flush with the black delrin base).	8.1
3. Turn the POWER switch ON. Verify the YELLOW indicator light is lit steady verifying the actuators are in the retracted position. A flashing YELLOW light indicates the batteries are low and must be replaced.	6.0
4. Attach the actuator to the breaker.	8.2
5. If the intended action is to close the circuit breaker, charge the breaker by operating the spring charging handle the required number of strokes. Verify the "Charged" flag is visible on the breaker "Closing Springs" indicator.	
6. Ensure you are at a safe distance from the circuit breaker that is to be operated. Note: The user must determine the safe distance based on NFPA 70E requirements.	
7. When ready to operate the breaker, press and hold the ENABLE button.	6.1
8. While holding the ENABLE button, operate the appropriate button to TRIP or CLOSE the breaker.	6.1
9. Release the ENABLE button and control button after the breaker has operated.	6.1
10. Remove the actuator from the breaker.	8.3

10.0 Care and Storage

10.1 Cleaning the magnets

Over a period of time, the magnets may attract ferrous debris. Exercise care to avoid setting the actuator where the magnets might attract debris. If this does occur, use a paper towel or nylon bristle brush to clean the face of the magnets. Masking tape can also be used to remove small dirt particles from magnets. Keeping the magnet faces clean ensures that maximum holding power is maintained.

10.2 Storage

- Remove all batteries from the control station if the device will not be used for longer than 6 months.
- Never store the batteries where the ambient temperature might exceed 110° F.
- Avoid getting the unit wet or storing it in a high humidity location. Store in a dry location.
- Store the unit in its carrying case.

11.0 Warranty

MarTek Ltd. guarantees all products manufactured by MarTek Ltd. only against defects in materials and/or workmanship for a period of twelve (12) months commencing on the date the product is received by the customer. THIS WARRANTY IS IN LIEU OF ALL OTHER EXPRESS OR IMPLIED WARRANTIES INCLUDING THOSE OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

MarTek Ltd. will, at its option and its cost (excluding shipping expenses), repair, replace or refund the purchase price of any product manufactured by MarTek Ltd. which has a defect in materials and/or workmanship. THIS IS CUSTOMER'S EXCLUSIVE REMEDY FOR BREACH OF WARRANTY. IN NO EVENT WILL MARTEK LTD'S LIABILITY FOR DAMAGES (WHETHER ARISING FROM BREACH OF CONTRACT OR WARRANTY, NEGLIGENCE, STRICT LIABILITY OR OTHERWISE) EXCEED THE PURCHASE PRICE OF THE PRODUCT CONCERNED NOR WILL MARTEK LTD. BE LIABLE FOR PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES (INCLUDING WITHOUT LIMITATION LOST PROFITS) EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

MarTek Ltd. reserves the right to disallow warranty repairs if the unit has been disassembled or misused, as determined by MarTek Ltd. in good faith. Please contact us at (800)-248-4958 for a return authorization.

MarTek Ltd.
4782 Chimney Drive
Charleston, WV 25302
1-304-965-9220
1-800-248-4958

12.0

Specifications

MECHANICAL

Holding magnets:	Two neodymium rare earth magnets rated @ 55.1 lbs force each.
Linear Actuators:	Up to 22 lbs. force.
Projected life:	20,000 operations

ELECTRICAL

Operating voltage:	12 volts DC
Fuse:	3 amp, quick-blow, AGC-3
Power supply:	8 AA alkaline disposable batteries. When used properly, one set of batteries should yield over 500 operations.
Control Cable:	30 feet in length (9.1 meters), 5-conductor, extra-flexible, PUR insulation. Optional 50' cable.
Controller:	Requires two-hand operation. The 'enable' button must be depressed while depressing the appropriate control button (Trip or Close). A programmable micro-controller manages control inputs, motor functions, and performs timing functions to protect the motor in a stalled condition. An intelligent 'H-bridge' motor driver provides start/stop motor functions. The H-bridge has integral thermal shutdown protection.

13.0 Troubleshooting Guide

1. The Chicken Switch will not operate. The yellow LED flashes rapidly whenever the Enable Button is depressed.
 - This is caused by a 'low voltage lockout'. Replace the batteries.
2. Yellow light does not light when depressing ENABLE button, the RED and GREEN lights work when operating control pushbuttons, but the actuator does not operate.

This can be caused by a couple of issues:

- a. Batteries are not fully seated in the battery holders or,
- b. the fuse is blown.

MarTek Ltd.

**4782 Chimney Drive
Charleston, WV 25302**

1-800-248-4958

www.chickenswitch.com

Chicken Switch is a Registered Trademark of MarTek Ltd.

US Patent 7,623,011

Copyright 2004-2016, MarTek Ltd. All rights reserved.