



MarTek Limited Arc Flash Safety

4782 Chimney Drive
Charleston, WV
P: (304) 965-9220
Sales@MartekLimited.com



SDR1

Remote Racking Operator

U.S. Patent Pending

Designed for:

Square-D Model 6 Closed Door Racking (CDR) Motor Control Centers

TAKE SAFETY FURTHER.

RACK IN. RACK OUT.

Product Information:

The SDR1 is designed to remotely rack the Square-D Model 6 Closed Door Racking Motor Control Center by Schneider Electric. The racking mechanism is temporarily installed over the CDR push button and racking handle socket. The lightweight unit easily and securely clamps onto the MCC with the simple engagement of the locking lever. The 30' cable and remote control operator allows the user to be positioned outside of the Arc Flash Hazard Zone while operating the Motor Control Center.

What do you get?

This model includes the actuator, 30' cable, GFCI AC adapter, instruction manual, and digital display control unit within a durable Pelican-brand carrying case.



ATTACHES/DETACHES IN SECONDS



SPECIFICATIONS:

Power Source	120 V, 60hz power source. GFCI AC Adapter
Operating Cable	30' cable
Projected Life	10,000+ operations
Average Cycle Time	9.56 seconds
Weight	SDR1 Actuator - 2.8lbs / 1.27kg Complete unit with carrying case - 11.75lbs / 5.33kg
Max. Operating Torque	100 in.lb.
Dimensions	SDR1 Actuator - 7.125" x 3.5" X 3"
Carrying case	Manufactured by Pelican with the following features: Two Press & Pull Latches Double-layered, Soft-grip Handle Two Pad-lockable Hasps Vortex® Valve Flush Powerful Hinges Lightweight Strong HPX® Resin Watertight Meets airline regulations for carry-on luggage Exterior Dimensions 16.20" x 12.70" x 6.60" (41.1 x 32.2 x 16.8cm)

ORDERING INFORMATION:

Complete Part Number:

- SDR1 - 30C (*SDR1 Actuator with 30' Cable*)

Contact:

- Your Schneider Electric / Square D Representative
or:
- MarTek Limited at 800-248-4958 / sales@marteklimited.com

MARTEK

Arc Flash Safety